

# ***M6VLQ Grand BIOS Setup***

---

<b>BIOS Setup.....</b>	<b>1</b>
1 Main Menu.....	3
2 Standard CMOS Features.....	6
3 Advanced BIOS Features.....	9
4 Advanced Chipset Features.....	12
5 Integrated Peripherals .....	16
6 Power Management Setup.....	20
7 PnP/PCI Configurations .....	25
8 PC Health Status .....	28
9 Frequency Control.....	30

# ***M6VLQ Grand BIOS Setup***

---

## **BIOS Setup**

### **Introduction**

This manual discussed Award™ Setup program built into the ROM BIOS. The Setup program allows users to modify the basic system configuration. This special information is then stored in battery-backed RAM so that it retains the Setup information when the power is turned off.

The Award BIOS™ installed in your computer system's ROM (Read Only Memory) is a custom version of an industry standard BIOS. This means that it supports AMD® processor input/output system. The BIOS provides critical low-level support for standard devices such as disk drives and serial and parallel ports.

Adding important has customized the Award BIOS™, but nonstandard, features such as virus and password protection as well as special support for detailed fine-tuning of the chipset controlling the entire system.

The rest of this manual is intended to guide you through the process of configuring your system using Setup.

### **Plug and Play Support**

These AWARD BIOS supports the Plug and Play Version 1.0A specification. ESCD (Extended System Configuration Data) write is supported.

### **EPA Green PC Support**

This AWARD BIOS supports Version 1.03 of the EPA Green PC specification.

### **APM Support**

These AWARD BIOS supports Version 1.1&1.2 of the Advanced Power Management (APM) specification. Power management features are implemented via the System Management Interrupt (SMI). Sleep and Suspend power management modes are supported. Power to the hard disk drives and video monitors can be managed by this AWARD BIOS.

---

# M6VLQ Grand BIOS Setup

---

## PCI Bus Support

This AWARD BIOS also supports Version 2.1 of the Intel PCI (Peripheral Component Interconnect) local bus specification.

## DRAM Support

DDR SDRAM (Double Data Rate Synchronous DRAM) are supported.

## Supported CPUs

This AWARD BIOS supports the Intel® CPU.

## Using Setup

In general, you use the arrow keys to highlight items, press <Enter> to select, use the <PgUp> and <PgDn> keys to change entries, press <F1> for help and press <Esc> to quit. The following table provides more detail about how to navigate in the Setup program by using the keyboard.

Keystroke	Function
Up arrow	Move to previous item
Down arrow	Move to next item
Left arrow	Move to the item on the left (menu bar)
Right arrow	Move to the item on the right (menu bar)
Move Enter	Move to the item you desired
PgUp key	Increase the numeric value or make changes
PgDn key	Decrease the numeric value or make changes
+ Key	Increase the numeric value or make changes
- Key	Decrease the numeric value or make changes
Esc key	Main Menu – Quit and not save changes into CMOS Status Page Setup Menu and Option Page Setup Menu – Exit Current page and return to Main Menu
F1 key	General help on Setup navigation keys
F5 key	Load previous values from CMOS
F7 key	Load the optimized defaults
F10 key	Save all the CMOS changes and exit

---

# M6VLQ Grand BIOS Setup

---

## 1 Main Menu

Once you enter Award BIOS™ CMOS Setup Utility, the Main Menu will appear on the screen. The Main Menu allows you to select from several setup functions. Use the arrow keys to select among the items and press <Enter> to accept and enter the sub-menu.

**!! WARNING !!**

The information about BIOS defaults on manual (**Figure 1,2,3,4,5,6,7,8,9**) is just for reference, please refer to the BIOS installed on board, for update information.

■ Figure 1. Main Menu



### Standard CMOS Features

This submenu contains industry standard configurable options.

### Advanced BIOS Features

This submenu allows you to configure enhanced features of the BIOS.

### Advanced Chipset Features

This submenu allows you to configure special chipset features.

### Integrated Peripherals

This submenu allows you to configure certain IDE hard drive options and Programmed

# ***M6VLQ Grand BIOS Setup***

---

Input/ Output features.

## **Power Management Setup**

This submenu allows you to configure the power management features.

## **PnP/PCI Configurations**

This submenu allows you to configure certain “Plug and Play” and PCI options.

## **PC Health Status**

This submenu allows you to monitor the hardware of your system.

## **Frequency/ Voltage Control**

This submenu allows you to change CPU Vcore Voltage and CPU/PCI clock. **(However, this function is strongly recommended not to use. Not properly change the voltage and clock may cause CPU or M/B damage!)**

## **Load Optimized Defaults**

This selection allows you to reload the BIOS when the system is having problems particularly with the boot sequence. These configurations are factory settings optimized for this system. A confirmation message will be displayed before defaults are set.



Load Optimized Defaults (Y/N)? N

## **Set Supervisor Password**

Setting the supervisor password will prohibit everyone except the supervisor from making changes using the CMOS Setup Utility. You will be prompted with to enter a password.



Enter Password:

## **Set User Password**

If the Supervisor Password is not set, then the User Password will function in the same way as the Supervisor Password. If the Supervisor Password is set and the User Password is set, the “User” will only be able to view configurations but will not be able to change them.



Enter Password:

# ***M6VLQ Grand BIOS Setup***

---

## **Save & Exit Setup**

Save all configuration changes to CMOS(memory) and exit setup. Confirmation message will be displayed before proceeding.



SAVE to CMOS and EXIT (Y/N)? Y

## **Exit Without Saving**

Abandon all changes made during the current session and exit setup. Confirmation message will be displayed before proceeding.



Quit Without Saving (Y/N)? N

## **Upgrade BIOS**

This submenu allows you to upgrade bios.



BIOS UPDATE UTILITY (Y/N)? N

---


# M6VLQ Grand BIOS Setup

---

## 2 Standard CMOS Features

The items in Standard CMOS Setup Menu are divided into 10 categories. Each category includes no, one or more than one setup items. Use the arrow keys to highlight the item and then use the <PgUp> or <PgDn> keys to select the value you want in each item.

■ Figure 2. Standard CMOS Setup



---

# M6VLQ Grand BIOS Setup

---

## Main Menu Selections

This table shows the selections that you can make on the Main Menu.

Item	Options	Description
Date	mm : dd : yy	Set the system date. Note that the 'Day' automatically changes when you set the date.
Time	hh : mm : ss	Set the system internal clock.
IDE Primary Master	Options are in its sub menu.	Press <Enter> to enter the sub menu of detailed options
IDE Primary Slave	Options are in its sub menu.	Press <Enter> to enter the sub menu of detailed options.
IDE Secondary Master	Options are in its sub menu.	Press <Enter> to enter the sub menu of detailed options.
IDE Secondary Slave	Options are in its sub menu.	Press <Enter> to enter the sub menu of detailed options.
Drive A Drive B	360K, 5.25 in 1.2M, 5.25 in 720K, 3.5 in 1.44M, 3.5 in 2.88M, 3.5 in None	Select the type of floppy disk drive installed in your system.
Video	EGA/VGA CGA 40 CGA 80 MONO	Select the default video device.



## ***M6VLQ Grand BIOS Setup***

---

<b>Item</b>	<b>Options</b>	<b>Description</b>
Halt On	All Errors No Errors All, but Keyboard All, but Diskette All, but Disk/ Key	Select the situation in which you want the BIOS to stop the POST process and notify you.
Base Memory	N/A	Displays the amount of conventional memory detected during boot up.
Extended Memory	N/A	Displays the amount of extended memory detected during boot up.
Total Memory	N/A	Displays the total memory available in the system.


---

# M6VLQ Grand BIOS Setup

---

## 3 Advanced BIOS Features

■ Figure 3. Advanced BIOS Setup



### Boot Seq & Floppy Setup

#### **First/ Second/ Third/ Boot Other Device**

These BIOS attempt to load the operating system from the device in the sequence selected in these items.

**The Choices:** Floppy, LS120, HDD-0, SCSI, CDROM, HDD-1, HDD-2, HDD-3, ZIP100, USB-FDD, USB-ZIP, USB-CDROM, USB-HDD, LAN, HPT370, Disabled, Enabled.

#### **Swap Floppy Drive**

For systems with two floppy drives, this option allows you to swap logical drive assignments.

**The Choices:** Disabled (default), Enabled.

#### **Boot Up Floppy Seek**

Enabling this option will test the floppy drives to determine if they have 40 or 80 tracks. Disabling this option reduces the time it takes to boot-up.

**The Choices:** Disabled, Enabled (default).

# ***M6VLQ Grand BIOS Setup***

---

## **Cache & Shadow Setup**

### **CPU Internal Cache**

Depending on the CPU/chipset in use, you may be able to increase memory access time with this option.

#### **The Choices:**

<b>Enabled</b> (default)	Enable cache.
Disabled	Disable cache.

### **External Cache**

This option you to enable or disable "Level 2" secondary cache on the CPU, which may improve performance.

#### **The Choices:**

<b>Enabled</b> (default)	Enable cache.
Disabled	Disable cache.

### **CPU L2 Cache ECC Checking**

This item allows you to enable/disable CPU L2 Cache ECC Checking.

**The Choices:** **Enabled** (default), Disabled.

### **Video BIOS Shadow**

Determines whether video BIOS will be copied to RAM for faster execution.

#### **The Choices:**

<b>Enabled</b> (default)	Optional ROM is enabled.
Disabled	Optional ROM is disabled.

## **Virus Warning**

This option allows you to choose the Virus Warning feature that is used to protect the IDE Hard Disk boot sector. If this function is enabled and an attempt is made to write to the boot sector, BIOS will display a warning message on the screen and sound an alarm beep.

<b>Disabled</b> (default)	Virus protection is disabled.
Enabled	Virus protection is activated.

## **Processor Number feature**

This item allows you enable or disable processor number feature.

**The Choices:** **Enabled** (default), Disabled.

## **Quick Power On Self Test**

Enabling this option will cause an abridged version of the Power On Self-Test (POST) to execute after you power up the computer.

<b>Enabled</b> (default)	Enable quick POST.
Disabled	Normal POST.

## **Boot Up NumLock Status**

Selects the NumLock. State after power on.

# ***M6VLQ Grand BIOS Setup***

---

**On** (default)  
**Off**

Numpad is number keys.  
Numpad is arrow keys.

## **Gate A20 Option**

Select if chipset or keyboard controller should control Gate A20.

**Normal**

A pin in the keyboard controller controls Gate A20.

**Fast** (default)

Lets chipset control Gate A20.

## **Typematic Rate Setting**

When a key is held down, the keystroke will repeat at a rate determined by the keyboard controller. When enabled, the typematic rate and typematic delay can be configured.

**The Choices:** **Disabled** (default), Enabled.

## **Typematic Rate (Chars/Sec)**

Sets the rate at which a keystroke is repeated when you hold the key down.

**The Choices:** **6** (default), 8,10,12,15,20,24,30.

## **Typematic Delay (Msec)**

Sets the delay time after the key is held down before it begins to repeat the keystroke.

**The Choices:** **250** (default), 500,750,1000.

## **Security Option**

This option will enable only individuals with passwords to bring the system online and/or to use the CMOS Setup Utility.

**System**

A password is required for the system to boot and is also required to access the Setup Utility.

**Setup** (default)

A password is required to access the Setup Utility only.

This will only apply if passwords are set from the Setup main menu.

## **OS Select For DRAM > 64MB**

A choice other than Non-OS2 is only used for OS2 systems with memory exceeding 64MB.

**The Choices:** **Non-OS2** (default), OS2.

## **Summary Screen Show**

This item allows you to enable/ disable display the Summary Screen Show.

**The Choices:** **Disabled** (default), Enabled.

---


# M6VLQ Grand BIOS Setup

---

## 4 Advanced Chipset Features

This submenu allows you to configure the specific features of the chipset installed on your system. This chipset manage bus speeds and access to system memory resources, such as DRAM. It also coordinates communications with the PCI bus. The default settings that came with your system have been optimized and therefore should not be changed unless you are suspicious that the settings have been changed incorrectly.

■ **Figure 4. Advanced Chipset Setup**



### DRAM Clock/ Drive Control

To control the Clock. If you highlight the literal “Press Enter” next to the “DRAM Clock” label and then press the enter key, it will take you to a submenu with the following options:

#### **DRAM Clock**

This item determines DRAM clock following 100MHz, 133MHz or By SPD.

**The Choices:** 100MHz, 133MHz, **By SPD** (default).

#### **DRAM Timing**

This item determines DRAM clock/ timing follow SPD or not.

**The Choices:** **By SPD** (default), Manual.

#### **DRAM CAS Latency**

When DRAM is installed, the number of clock cycles of CAS latency depends on the DRAM timing.

**The Choices:** **2.5** (default), 2.

# **M6VLQ Grand BIOS Setup**

---

## **Bank Interleave**

This item allows you to enable or disable the bank interleave feature.

**The Choices:** **Disabled** (default).

## **Precharge to Active (Trp)**

This item allows you to specify the delay from precharge command to activate command.

**The Choices:** 2T, 3T (default).

## **Active to Precharge (Tras)**

This item allows you to specify the minimum bank active time.

**The Choices:** 7T, 6T (default).

## **Active to CMD (Trcd)**

Use this item to specify the delay from the activation of a bank to the time that a read or write command is accepted.

**The Choices:** 2T, 3T (default).

## **DRAM Command Rate**

This item controls clock cycle that must occur between the last valid write operation and the next command.

**The Choices:** 1T Command, 2T Command (default).

## **AGP & P2P Bridge Control**

If you highlight the literal “Press Enter” next to the “AGP & P2P Bridge Control” label and then press the enter key, it will take you a submenu with the following options:

### **AGP Aperture Size**

Select the size of the Accelerated Graphics Port (AGP) aperture. The aperture is a portion of the PCI memory address range dedicated for graphics memory address space. Host cycles that hit the aperture range are forwarded to the AGP without any translation.

**The Choices:** 64M (default), 256M, 128M, 32M, 16M, 8M, 4M.

### **AGP Mode**

This item allows you to select the AGP Mode.

**The Choices:** 4X (default), 2X, 1X.

### **AGP Driving Control**

By choosing “Auto” the system BIOS will the AGP output Buffer Drive strength P Ctrl by AGP Card. By choosing “Manual”, it allows user to set AGP output Buffer Drive strength P Ctrl by manual.

**The Choices:** Auto (default), Manual.

### **AGP Driving Value**

While AGP driving control item set to “Manual”, it allows user to set AGP driving.

**The Choices:** DA (default).

# ***M6VLQ Grand BIOS Setup***

---

## **AGP Master 1 WS Write**

**The Choices:** Enabled, **Disabled** (default).

## **AGP Master 1 WS Read**

When Enabled, read to the AGP (Accelerated Graphics Port) are executed with one wait states.

**The Choices:** **Disabled** (default), Enabled.

## **CPU & PCI Bus Control**

If you highlight the literal “Press Enter” next to the “CPU & PCI Bus Control” label and then press the enter key, it will take you a submenu with the following options:

### **CPU to PCI Write Buffer**

When enabled, up to four Dwords of data. Can be written to the PCI bus without interrupting the CPU. When disabled, a write buffer is not used and the CPU read cycle will not be completed until the PCI bus signals that it is ready to receive the data.

**The Choices:** **Enabled** (default), Disabled.

### **PCI Master 0 WS Write**

When Enabled, writes to the PCI bus are executed with zero-wait states.

**The Choices:** **Enabled** (default), Disabled.

### **PCI Delay Transaction**

The chipset has an embedded 32-bit posted write buffer to support delay transactions cycles. Select Enabled to support compliance with PCI specification.

**The Choices:** Disabled, **Enabled** (default).

## **Memory Hole At 15M-16M**

You can reserve this area of system memory for ISA adapter ROM. When this area is reserved it cannot be cached. The user information of peripherals that need to use this area of system memory usually discussed their memory requirements.

**The Choices:** **Disabled** (default), Enabled.

## **System BIOS Cacheable**

Selecting the “Enabled” option allows caching of the system BIOS ROM at F0000h-FFFFFh which can improve system performance. However, any programs writing to this area of memory will cause conflicts and result in system errors.

**The Choices:** Enabled, **Disabled** (default).

## **Video RAM Cacheable**

Enabling this option allows caching of the video RAM, resulting a better system performance. However, if any program writes to this memory area, a system error may result.

**The Choices:** **Disabled** (default), Enabled.

# ***M6VLQ Grand BIOS Setup***

---

## **VGA Share Memory Size**

This item allows you to select the VGA share memory size.

**The Choices:** 32M (default), 16M, 8M, Disabled.

## **Memory Parity/ ECC Check**

This item allows you to enable or disable memory parity/ ECC checking.

**The Choices:** Disabled (default), Enabled.




---

# M6VLQ Grand BIOS Setup

---

## 5 Integrated Peripherals

■ Figure 5. Integrated Peripherals



### USB 2.0 Support

This item allows you to enable or disable USB 2.0 supports.

**The Choices:** Enabled (default), Disabled.

### VIA Onchip IDE Device

The chipset contains a PCI IDE interface with support for two IDE channels.

Select “Enabled” to activate the first and / or second IDE interface. If you install a primary and / or secondary add-in IDE interface, select “Disabled” to deactivate an interface. If you highlight the literal “Press Enter” next to the “Onchip IDE Control” label and then press the enter key, it will take you a submenu with the following options:

#### **OnChip IDE Channel 0/1**

The motherboard chipset contains a PCI IDE interface with support for two IDE channels. Select “Enabled” to activate the first and/or second IDE interface. Select “Disabled” to deactivate an interface if you are going to install a primary and/or secondary add-in IDE interface.

**The Choices:** Enabled (default), Disabled.

#### **IDE Prefetch Mode**

The “onboard” IDE drive interfaces supports IDE prefetching for faster drive access. If the interface does not support prefetching. If you install a primary

# ***M6VLQ Grand BIOS Setup***

---

and/or secondary add-in IDE interface, set this option to "Disabled".

**The Choices:** Enabled (default), Disabled.

## **Primary / Secondary Master / Slave PIO**

The IDE PIO (Programmed Input / Output) fields let you set a PIO mode (0-4) for each of the IDE devices that the onboard IDE interface supports. Modes 0 through 4 provides successively increased performance. In Auto mode, the system automatically determines the best mode for each device.

**The Choices:** Auto (default), Mode0, Mode1, Mode2, Mode3, Mode4.

## **IDE Primary / Secondary Master / Slave UDMA**

Ultra DMA/100 functionality can be implemented if it is supported by the IDE hard drives in your system. As well, your operating environment requires a DMA driver (Windows 95 OSR2 or a third party IDE bus master driver). If your hard drive and your system software both support Ultra DMA/100, select Auto to enable BIOS support.

**The Choices:** Auto (default), Disabled.

## **VIA OnChip PCI Device**

### **VIA-3058 AC97 Audio**

This item allows you to decide to enable/ disable to support AC97 Audio.

**The Choices:** Auto (default), Disabled.

### **VIA-3068 MC97 Modem**

This item allows you to decide to enable/ disable to support AC97 Modem.

**The Choices:** Auto (default), Disabled.

### **VIA-3043 OnChip LAN**

This item allows you to enable or disable the onboard LAN chip.

**The Choices:** Enabled (Default), Disabled.

### **Onboard LAN Boot ROM**

This item allows you to enable or disable the onboard LAN Boot ROM.

**The Choices:** Disabled (Default), Enabled.

## **Super IO Device**

Press Enter to configure the Super I/O Device.

### **Onboard FDC Controller**

Select Enabled if your system has a floppy disk controller (FDC) installed on the system board and you wish to use it. If install and FDC or the system has no floppy drive, select Disabled in this field.

**The Choices:** Enabled (default), Disabled.

### **Onboard Serial Port 1**

Select an address and corresponding interrupt for the first and second serial ports.

# ***M6VLQ Grand BIOS Setup***

---

**The Choices:** 3F8/IRQ4 (default), Disabled, Auto, 2F8/IRQ3, 3E8/IRQ4, 2E8/IRQ3.

## **UART Mode Select**

This item allows you to determine which Infrared (IR) function of onboard I/O chip.

**The Choices:** Normal(default), ASKIR, IrDA, SCR .

## **UR2 Duplex Mode**

Select the value required by the IR device connected to the IR port. Full-duplex mode permits simultaneous two-direction transmission. Half-duplex mode permits transmission in one direction only at a time.

**The Choices:** Half (default), Full.

## **Onboard Parallel Port**

This item allows you to determine access onboard parallel port controller with which I/O Address.

**The Choices:** 378/IRQ7 (default), 278/IRQ5, 3BC/IRQ7, Disabled.

## **Parallel Port Mode**

The default value is SPP.

<b>SPP</b> (default)	Using Parallel port as Standard Printer Port.
<b>EPP</b>	Using Parallel port as Enhanced Parallel Port.
<b>ECP</b>	Using Parallel port as Extended Capabilities Port
<b>ECP+EPP</b>	Using Parallel port as ECP & EPP mode.

## **ECP Mode Use DMA**

Select a DMA Channel for the port.

**The Choices:** 3 (default), 1.

## **Game Port Address**

Game Port I/O Address.

**The Choices:** 201 (default), 209, Disabled.

## **Midi Port Address**

Midi Port Base I/O Address.

**The Choices:** 330 (default), 300, Disabled.

## **Midi Port IRQ**

This determines the IRQ in which the Midi Port can use.

**The Choices:** 10 (default), 5.

## **Init Display First**

This item allows you to decide to active whether PCI Slot or on-chip VGA first.

**The Choices:** Onboard/AGP, **PCI Solt** (default).

# ***M6VLQ Grand BIOS Setup***

---

## **OnChip USB Controller**

This item allows you to set the onchip USB.

**The Choices:** **All Enabled** (default), All Disabled, 1&2 USB Port, 2&3 USB Port, 1&3 USB Port, 1 USB Port, 2 USB Port, 3 USB Port.

## **USB Keyboard Support**

The default value is Disabled.

Enabled

Enable USB Keyboard Support.

**Disabled** (default)

Disable USB Keyboard Support.

## **IDE HDD Block Mode**

Block mode is also called block transfer, multiple commands, or multiple sector read / write. If your IDE hard drive supports block mode (most new drives do), select Enabled for automatic detection of the optimal number of block mode (most new drives do), select Enabled for automatic detection of the optimal number of block read / write per sector where the drive can support.

**The Choices:** **Enabled** (default), Disabled.

---


# M6VLQ Grand BIOS Setup

---

## 6 Power Management Setup

The Power Management Setup Menu allows you to configure your system to utilize energy conservation and power up/power down features.

■ **Figure 6. Power Management Setup**



### ACPI function

This item displays the status of the Advanced Configuration and Power Management (ACPI).

**The Choices:** Enabled (default), Disabled.

### ACPI Suspend Type

The item allows you to select the suspend type under the ACPI operating system.

**The Choices:** S1 (POS) (default)   Power on Suspend  
S3 (STR)   Suspend to RAM  
S1 & S3   POS+STR

### Power Management

This category allows you to select the type (or degree) of power saving and is directly related to the following modes:

- 1.HDD Power Down.
- 2.Suspend Mode.

There are four options of Power Management, three of which have fixed mode settings

# ***M6VLQ Grand BIOS Setup***

---

## **Min. Power Saving**

Minimum power management.  
Suspend Mode = 1 hr.  
HDD Power Down = 15 min

## **Max. Power Saving**

Maximum power management only available for sl CPU's.  
Suspend Mode = 1 min.  
HDD Power Down = 1 min.

## **User Defined (default)**

Allows you to set each mode individually.  
When not disabled, each of the ranges are from 1 min. to 1 hr. except for HDD Power Down which ranges from 1 min. to 15 min. and disable.

## **Video Off Method**

This option determines the manner in which the monitor is goes blank.  
V/H SYNC+Blank

This selection will cause the system to turn off the vertical and horizontal synchronization ports and write blanks to the video buffer.

## **Blank Screen**

This option only writes blanks to the video buffer.

## **DPMS Support (default)**

Initial display power management signaling.

## **HDD Power Down**

When enabled, the hard disk drive will power down and after a set time of system inactivity. All other devices remain active.

**The Choices: Disabled** (default), 1 Min, 2 Min, 3 Min, 4 Min, 5 Min, 6 Min, 7 Min, 8 Min, 9 Min, 10 Min, 11 Min, 12 Min, 13 Min, 14 Min, 15Min.

## **Suspend Mode**

When enabled and after the set time of system inactivity, all devices except the CPU will be shut off.

**The Choices: Disabled** (default), 1Min, 2Min, 4Min, 8Min, 12Min, 20Min, 30Min, 40Min, 1Hour.

# ***M6VLQ Grand BIOS Setup***

---

## **Video Off Option**

This field determines when to activate the video off feature for monitor power management.

**The Choices:** Suspend→Off (default), Always on, All Modes→Off.

## **Video Off Method**

This option determines the manner in which the monitor is goes blank.

**V/H SYNC+Blank** (default)

This selection will cause the system to turn off the vertical and horizontal synchronization ports and write blanks to the video buffer.

**Blank Screen**

This option only writes blanks to the video buffer.

**DPMS**

Initial display power management signaling.

## **Modem Use IRQ**

This determines the IRQ, which can be applied in MODEM use.

**The Choices:** 3 (default), 4 / 5 / 7 / 9 / 10 / 11 / NA.

## **Soft-Off by PWR-BTTN**

Pressing the power button for more than 4 seconds forces the system to enter the Soft-Off state when the system has “hung.”

**The Choices:** Delay 4 Sec, **Instant-Off** (default).

## **Run VGABIOS if S3 Resume**

Choosing Enabled will make BIOS run VGA BIOS to initialize the VGA card when system wakes up from S3 state . The system time is shortened if you disable the function , but system will need AGP driver to initialize the card . So , if the AGP driver of the VGA card does not support the initialization feature , the display may work abnormally or not function after S3 .

**The Choices:**Auto (default), Yes, No.

## **State After Power Failure**

This field determines the action the system will automatically take when power is restored to a system that had lost power previously without any subsequent manual intervention. There are 3 sources that provide current to the CMOS area that retains these Power-On instructions; the motherboard battery (3V), the Power Supply (5VSB), and the Power Supply (3.3V). While AC is not supplying power, the motherboard uses the motherboard battery (3V). If AC power is supplied and the Power Supply is not turned on, 5VSB from the Power Supply is used. When the Power Supply is eventually turned on 3.3V from the Power Supply will be used.

---

# M6VLQ Grand BIOS Setup

---

The Choices: Auto, On, Off (default).

## IRQ/ Event Activity Detect

If you highlight the literal “ Press Enter” next to the “IRQ/ Event Activity Detect” label and then press the enter key, it will take you to a submenu with the following options:

### **VGA**

When set to on, any event occurring at a VGA port will awaken a system which has been powered down.

The Choices: Off (default), On.

### **LPT & COM**

When set to **On**, any event occurring at a LPT/COM Port will awaken a system which has been powered down.

The Choices: LPT/COM (default), COM, LPT, NONE.

### **HDD & FDD**

When set to On (default), any event occurring at a hard or floppy drive will awaken a system which has been powered down.

The Choices: On (default), Off.

### **PCI MASTER**

When set to On, any event occurring at PCI will awaken a system which has been powered down.

The Choices: Off (default), On.

### **PowerOn by PCI Card**

This item allows you to enable or disable Power on by PCI Card.

The Choices: Disabled (default), Enabled.

### **Modem Ring Resume**

This item allows you to enable or disable modem ring resume.

The Choices: Disabled (default), Enabled.

### **Wake Up On LAN/Ring**

To use this function, you need a LAN add-on card which support power on function. It should also support the wake-up on LAN jump.

The Choices: Disabled (default), Enabled.

### **RTC Alarm Resume**

When “Enabled”, you can set the date and time at which the RTC (real-time clock) alarm awakens the system from Suspend mode.

The Choices: Disabled (default), Enabled.

### **Date (of Month)**

You can choose which month the system will boot up.

**Resume Time (hh: mm: ss)** You can choose the hour, minute and second the



# ***M6VLQ Grand BIOS Setup***

---

system will boot up.

## **Primary INTR**

When set to ON (default), any event occurring at Primary INTR will awaken a system, which has been powered down.

## **IRQs Activity Monitoring**

When set to ON (default), any event occurring at Primary INTR will awaken a system which has been powered down.

The following is a list of IRQ, Inter ReQuest, which can be exempted much as the COM ports and LPT ports above can. When an I/P device wants to gain the attention of the operating system, it signals this by causing an IRQ to occur. When the operating system is ready to respond to the request, it interrupts itself and performs the services.

As above, the choices are On and Off. Off is the default.

When set On, activity will neither prevent the system from going into a power management mode nor awaken it.

### **Primary INTR**

**IRQ3 (COM2)**

**IRQ4 (COM1)**

**IRQ5 (LPT2)**

**IRQ6 (Floppy Disk)**

**IRQ7 (LPT1)**

**IRQ8 (RTC Alarm)**

**IRQ9 (IRQ2 Redir)**

**IRQ10 (Reserved)**

**IRQ11 (Reserved)**

**IRQ12 (PS2/Mouse)**

**IRQ13 (Coprocessor)**

**IRQ14 (Hard Disk)**

**IRQ15 (Reserved)**

---


# M6VLQ Grand BIOS Setup

---

## 7 PnP/PCI Configurations

This section describes configuring the PCI bus system. PCI, or Personal Computer Interconnect, is a system which allows I/O devices to operate at speeds nearing the speed of the CPU itself uses when communicating with its own special components. This section covers some very technical items and it is strongly recommended that only experienced users should make any changes to the default settings.

■ **Figure 7. PnP/PCI Configurations**



### **PNP OS Installed**

When set to "Yes", BIOS will only initialize the PnP cards used for booting (VGA, IDE, SCSI). The rest of the cards will be initialized by the PnP operating systems, like Windows<sup>TM</sup>95. When set to "No", BIOS will initialize all the PnP cards. Therefore for non-PnP operating system (DOS, Netware<sup>TM</sup>), this option must set to "No".

**The Choices:** No (default), Yes.

### **Reset Configuration Data**

The system BIOS supports the PnP feature which requires the system to record which resources are assigned and protects resources from conflict. Every peripheral device has a node, which is called ESCD. This node records which resources are assigned to it. The system needs to record and update ESCD to the memory locations. These locations (4K) are reserved in the system BIOS. If the Disabled (default) option is chosen, the system's ESCD will update only when the new configuration varies from the last one. If the Enabled

---

# M6VLQ Grand BIOS Setup

---

option is chosen, the system is forced to update ESCDs and then is automatically set to the "Disabled" mode.

The above settings will be shown on the screen only if "Manual" is chosen for the resources controlled by function.

Legacy is the term, which signifies that a resource is assigned to the ISA Bus and provides non-PnP ISA add-on cards. PCI / ISA PnP signifies that a resource is assigned to the PCI Bus or provides for ISA PnP add-on cards and peripherals.

**The Choices:** Disabled (default), Enabled.

## **Resources Controlled By**

By Choosing "**Auto(ESCD)**" (default), the system BIOS will detect the system resources and automatically assign the relative IRQ and DMA channel for each peripheral. By Choosing "Manual", the user will need to assign IRQ & DMA for add-on cards. Be sure that there are no IRQ/DMA and I/O port conflicts.

## **IRQ Resources**

This submenu will allow you to assign each system interrupt a type, depending on the type of device using the interrupt. When you press the "Press Enter" tag, you will be directed to a submenu that will allow you to configure the system interrupts. This is only configurable when "Resources Controlled By" is set to "Manual".

IRQ-3	assigned to	PCI Device
IRQ-4	assigned to	PCI Device
IRQ-5	assigned to	PCI Device
IRQ-7	assigned to	PCI Device
IRQ-9	assigned to	PCI Device
IRQ-10	assigned to	PCI Device
IRQ-11	assigned to	PCI Device
IRQ-12	assigned to	PCI Device
IRQ-14	assigned to	PCI Device
IRQ-15	assigned to	PCI Device

## **PCI / VGA Palette Snoop**

Choose Disabled or Enabled. Some graphic controllers which are not VGA compatible take the output from a VGA controller and map it to their display as a way to provide boot information and VGA compatibility.

However, the color information coming from the VGA controller is drawn from the palette table inside the VGA controller to generate the proper colors, and the graphic controller needs to know what is in the palette of the VGA controller. To do this, the non-VGA graphic controller watches for the Write access to the VGA palette and registers the snoop data. In PCI based systems, where the VGA controller is on the PCI bus and a non-VGA graphic controller is on an ISA bus, the Write Access to the palette will not show up on the

# ***M6VLQ Grand BIOS Setup***

---

ISA bus if the PCI VGA controller responds to the Write.

In this case, the PCI VGA controller should not respond to the Write, it should only snoop the data and permit the access to be forwarded to the ISA bus. The non-VGA ISA graphic controller can then snoop the data on the ISA bus. Unless you have the above situation, you should disable this option.

<b>Disabled</b> (default)	Disables the function.
Enabled	Enables the function.

## **Assign IRQ For USB**

Lets the user choose which IRQ to assign for USB.

**The Choices:** Enabled (default), Disabled.

## **Assign IRQ For VGA**


Lets the user choose which IRQ to assign for the VGA.

**The Choices:** Enabled (default), Disabled.

# M6VLQ Grand BIOS Setup

## 8 PC Health Status

■ Figure 8. PC Health Status



### Shutdown Temperature

This item allows you to set up the CPU shutdown Temperature. This item only effective under Windows 98 ACPI mode.

**The Choices:** 60°C/ 140°F, 65°C/ 149°F, 70°C/ 158°F, Disabled (default).

### CPU Vcore/ +3.3V/ +5V/ +12V/ -12V/ -5V/ 5V (SB)/ Battery Voltage

Detect the system's voltage status automatically.

### Current CPU Temp

Show you the current CPU temperature.

### Current CPU FAN Speed

This field displays the current CPU FAN speed.

### Current SYS FAN Speed

This field displays the current SYS FAN speed.

# ***M6VLQ Grand BIOS Setup***

---

## **Show H/W Monitor in POST**

If your computer contains a monitoring system, it will show PC health status during POST stage.  
The item offers several delay times to select the one you want.

**The Choices:** **Enabled** (default), Disabled.

## **Chassis Open Warning**

This item allows you to enable or disable Chassis Open Warning beep.

**The Choices:** **Disabled** (Default), Enabled.


---

# M6VLQ Grand BIOS Setup

---

## 9 Frequency Control

■ Figure 9. Frequency Control



### VIA C3 Clock Ratio

This item allows you to select the C3 clock ratio.

**The Choices:** Default (default), x3, x3.5, x4, x4.5, x5, x5.5, x6, x6.5, x7, x8, x9, x10, x9.5, x12, x8.5, x10.5, x11, x12, x12.5, x13, x14, x14.5, x15, x15.5, x16.

### CPU Voltage

This item allows you to select CPU Voltage Regulator.

**The Choices:** Default (default), +5.1%, +3.4%, +1.7%.

### DDR Voltage

This item allows you to select DDR Voltage Regulator.

**The Choices:** 2.6V (default), 2.7V, 2.8V.

### Auto Detect PCI/ DIMM Clk

This item allows you to enable or disable auto Detect PCI/ DIMM Clock.

**The Choices:** Enabled (default), Disabled.

# ***M6VLQ Grand BIOS Setup***

---

## **CPU Clock**

This item allows you to select CPU Clock, and CPU over clocking.



If unfortunately, the system's frequency that you are selected is not functioning, there are two methods of booting-up the system.

Method 1: Clear the COMS data by setting the JCOMS1 ((2-3) closed)) as "ON" status. All the CMOS data will be loaded as defaults setting.

Method 2: Press the <Insert> key and Power button simultaneously, after that keep-on pressing the <Insert> key until the power-on screen showed. This action will boot-up the system according to FSB of the processor.

※ **It's strongly recommended to set CPU Vcore and clock in default setting. If the CPU Vcore and clock are not in default setting, it may cause CPU or M/B damage.**

## **Intel CPU Ratio**

This item allows you to select the CPU Ratio.

**The Choices: Default** (default), x3, x3.5, x4, x4.5, x5, x5.5, x6, x6.5, x7, x7.5, x8, x8.5, x9, x9.5, x10, x10.5, x11, x11.5, x12, x13, x14, x15, x16.